

COMPATIBLE TRANSFORMERS FOR 12V SYSTEMS

Below is the compatible list of transformers

1) For Systems WITHOUT a dimmer

Brand	Transformer Model	Input Voltage (VAC/HZ)	Wattage (W)	Type	MR16s per Transformer (no dimmer connected)					
					1	2	3	4	5	6
Advance	71A9743	120VAC, 60Hz	70	MT	G	G	G	G	G	G
	HUA1200600X2L	120VAC, 60Hz	60	ET	G	G	G	G	G	G
	250LED100W	120VAC, 60Hz	100	ET	G	G	G	G	G	G
	250LED10W	120VAC, 60Hz	10	ET	G	N/A	N/A	N/A	N/A	N/A
	250AT075T	120VAC, 60Hz	75	MT	G	G	G	G	G	G
Hatch	RS12-15M-LED	120VAC, 50-60Hz	15	ET	F	F	G	N/A	N/A	N/A
	PS12-20L	120VAC, 60Hz	20	ET	G	G	G	G	N/A	N/A
	RS12-30M-LED	120VAC, 50-60Hz	30	ET	G	G	G	G	G	G
	RS12-60M	120VAC, 50-60Hz	60	ET	G	G	G	G	G	G
	VS12-60W	120VAC, 50-60Hz	60	ET	G	G	G	G	G	G
	VS12-60WD	120VAC, 50-60Hz	60	ET	G	G	G	G	F	G
	RS12-80M	120VAC, 50-60Hz	80	ET	G	G	G	G	G	G
	RS12-60M-LED	120VAC, 50-60Hz	60	ET	G	G	G	G	G	G
LCI	i60e	230VAC, 50-60Hz	60	ET	G	G	G	G	G	G
Lighttech	LET-60***	120VAC, 50-60Hz	60	ET	F	F	F	F	F	F
	LET-75***	120VAC, 50-60Hz	75	ET	F	F	F	F	F	F
Ligo	E12SC50SA	230VAC	50	MT	G	G	G	G	G	G
Lumex	MTR50/12EN-61558	220VAC, 50Hz	50	MT	G	G	G	G	G	G
MDL	319-0103	120VAC, 50-60Hz	10	ET	G	N/A	N/A	N/A	N/A	N/A
Mirano	BLNET-L50C 50W	220VAC, 50Hz	50	ET	G	G	G	G	G	G
Niko	320-00112	230VAC, 50Hz	105	ET	G	G	G	G	G	G
Nobile	EN-60D***	230VAC, 50-60Hz	60	ET	G	F	F	F	F	F
	EN60D2***	230VAC, 50-60Hz	60	ET	F	F	G	F	F	F
	EB-70D***	230VAC, 50-60Hz	70	ET	F	F	F	G	G	G
	EN-80D	230VAC, 50-60Hz	80	ET	G	G	G	G	G	G
	EN-80D2***	230VAC, 50-60Hz	80	ET	G	G	G	G	F	F
	EN-110D	230VAC, 50-60Hz	110	ET	G	G	G	G	G	G
OSRAM	HTM 150/230-240	230VAC, 50-60Hz	150	ET	G	G	G	G	G	G
	Phillips	Primaline 105 230-240	230-240VAC, 50-60Hz	105	ET	G	G	G	G	G
Sunrise	Xitanium 10W Dimmable	220-240VAC, 50-60Hz	10	ET	G	N/A	N/A	N/A	N/A	N/A
	H0050-497	120VAC, 50-60Hz	50	MT	G	G	G	G	G	G
Tridonic	VIPER 22176074***	230V-240VAC, 50-60Hz	105	ET	G	G	G	G	G	F
	VIPER 22176072***	230V-240VAC, 50-60Hz	105	ET	G	G	F	F	F	F
VadsBO	SET70RE-1	220-240AC, 50Hz	70	ET	G	G	G	G	G	G
Vossloh Schwabe	EST 70/12.380	230V-240VAC, 50-60Hz	70	ET	G	G	G	G	G	G
	EST 105/12.381	230V-240VAC, 50-60Hz	105	ET	G	G	G	G	G	G
	EST 150/12.622	230V-240VAC, 50-60Hz	150	ET	G	G	G	G	G	G
WAC	EN-12100-R-AR	120VAC, 50-60Hz	100	ET	G	G	G	G	G	G
Wang	WH-601E2CA-2L	120VAC, 60Hz	60	ET	G	G	G	G	G	G
*** Not recommended for use with dimmer										
Symbol / Description		ET / Electronic Transformer		MT / Magnetic Transformer			F / Flickers			
		N/A / Exceeds Transformer		G / Good / Recommended Power						